

### Control Stations



XAL-B211H29



XAL-B213



XAL-B114



XAL-B116



XAL-B361H29



XAL-B373

Start-stop function (light grey lid with dark grey base)

Description	Scheme	Contact type	Marking on legend	Marking on button	Reference	Weight (kg)
2 spring return pushbutton 1 flush green 1 flush red		N/O+N/C	Start Stop	- -	XAL-B211H29	0.165
			-	I O	XAL-B213	0.165
			-	Start Stop	XAL-B215	0.165
1 selector switch 2 position stay put standard black handle		N/O	Start Stop	- -	XAL-B132H29	0.125
			O I	- -	XAL-B314	0.125
1 selector switch key operated (key n° 455) 2 position stay put key withdrawal from LH position		N/C	Start Stop	- -	XAL-B142H29	0.150
			O I	- -	XAL-B144	0.150

Start-stop function (light grey lid with dark grey base)

Description	Scheme	Contact type	Marking on legend	Marking on button	Reference	Weight (kg)
1 red pilot light direct supply 130V bulb not included (1) + 2 spring return pushbuttons 1 flush green 1 flush red		N/O+N/C	Start Stop	- -	XAL-B361H29	0.200
			-	I O	XAL-B363	0.200
			-	Start Stop	XAL-B366	0.200
1 red pilot light 230V supply direct through resistor bulb with BA 9s base fitting-130V (included) + 2 spring return pushbuttons 1 flush green 1 flush red		N/O+N/C	Start Stop	- -	XAL-B371H29	0.205
			-	I O	XAL-B373	0.205
			-	Start Stop	XAL-B376	0.205

(1) Bulb types for use with direct supply:

- incandescent bulb, BA 9s base fitting:  $U \leq 130V$ , maximum power 2.6W, maximum length: 28mm
- neon bulb, BA 9s base fitting:  $110V \leq U \leq 380V$ . Please consult our local representatives or agents